



TRANSFORMER FUSE / M.C.B. PRIMARY PROTECTION

VA	Pri Volts	Amps	Fuse Type T	MCB type C	MCB Type D	Pri volts	Amps	Fuse	MCB Type C	MCB Type D
50	230	0.21	0.5	1	1	400	0.12	0.315		
75	230	0.32	0.8	1	1	400	0.18	0.5	1	1
100	230	0.43	0.8	1	1	400	0.25	0.5	1	1
150	230	0.65	1.25	2	1	400	0.37	0.8	1	1
200	230	0.87	2	2	2	400	0.50	1.25	1	1
250	230	1.08	2	4	2	400	0.62	1.25	2	1
300	230	1.30	3.15	4	2	400	0.75	2	2	2
400	230	1.74	3.15	4	4	400	1.00	2	4	2
500	230	2.17	4	6	4	400	1.25	3.15	4	2
750	230	3.26	6.3	10	6	400	1.87	4	4	4
1000	230	4.34	8	10	10	400	2.50	6.3	6	4
1250	230	5.43	10	16	10	400	3.12	6.3	10	6
1500	230	6.52	16	16	10	400	3.75	8	10	6
2000	230	8.69	16	20	16	400	5.00	10	16	10
2500	230	10.86	20	32	20	400	6.25	16	16	10
3000	230	13.04	25	32	20	400	7.50	16	16	16
4000	230	17.39	32	40	32	400	10.00	20	32	16
5000	230	21.74	40	63	40	400	12.50	25	32	20
6000	230	26.08	50	63	40	400	15.00	32	40	32
7500	230	32.60	63	80	63	400	18.75	40	63	32
10000	230	43.47	80		80	400	25.00	50	63	40
12500	230	54.34	100			400	31.25	63	80	63
15000	230	65.21	125			400	37.50	80		63
20000	230	86.95	160			400	50.00	100		80
25000	230	108.69	200			400	62.50	125		
30000	230	130.43				400	75.00	160		
40000	230	173.91				400	100.00	200		
50000	230	217.39				400	125.00			

Note :- These figures are for guidance only.